



Voyager 1300-1700 watts

The flagship of our domestic stand-alone inverter range is quality all the way.

Its thoughtful chassis design makes mounting and installation a breeze, and a simple yet effective LED layout tells you operating status at a glance.

This design incorporates flat line efficiency technology for excellent efficiency and minimum battery draw—even with the smallest load.

The Voyager allows you to hardwire the AC connections making it ideal for domestic home systems, large motorhomes, boats and service vehicles.

The conservative design approach of the Voyager ensures reliable performance year after year.



FEATURES

- sine wave output runs all appliances
- continuously rated
- LED indicators
- excellent short term and surge ratings
- extra-heavy duty, low loss battery cables
- fast and flexible installation
- standard power point, with optional safety switch / AC circuit breaker
- non-corrosive chassis, with high degree of recyclability
- ruggedly built to withstand the rigours of the road
- adjustable load-detection
- export ready, 60 Hz output on request
- impending shutdown output

APPLICATIONS

- microwave ovens
- large power tools
- washing machines
- fridges
- computers
- toasters
- hair dryers
- evaporative coolers
- pumps

WHERE TO USE

- domestic homes
- motorhomes
- boats
- larger service vehicles



SPECIFICATIONS

VOYAGER	SEAP-12-1K3A	SEAP-24-1K7	SEAP-48-1K7*
Battery input (V)	12	24	48
Continuous power (W)	1300	1700	1700
5-minute rating (W)	2200	3000	3000
Surge power (W)	4000	5000	4500
Peak efficiency (%)	91	94	94
Load detection (W)	1-20	1-20	1-20
Minimum battery size (A.h)	250	300	300
Weight (kg)	21.0	19.5	19.0
Size (mm) LxWxD	460 x 300 x 165		

* All specifications are at 30°C and unity power factor. See page xx for further specifications. * Indent item only