



Piccolo 150-250 watts



The Piccolo is the smallest sine wave inverter in our range.

Simple to use, this unit has proven itself over the years as one of the best performing and most reliable models in the small inverter market.

The Piccolo stands tall in a market full of cheaper imitations. The surge performance of this unit will easily out perform higher rated competitors products allowing it to run most televisions.

The tiny battery draw of just 0.17 amps (12-volt model) maximises battery life between charging.

Wherever you want to run appliances up to 250 watts, the Piccolo is the answer.

WHERE TO USE

caravans
motorhomes
mobile offices
trades and service vehicles
4WD vehicles
boats

APPLICATIONS

televisions (to 16in/40cm)
recharging batteries
laptop computers
sleep apnea machines
electric shaver
fax machines
small stereos
electric blankets

FEATURES

- sine wave output runs all appliances
- compact size
- outstanding reliability
- thermostatically controlled fan keeps unit cooler
- dual coloured LED status indicator
- simple to connect—simply plug into the cigarette lighter (12-volt model)
- continuously rated—delivers the power you pay for
- no electrician required for installation



SPECIFICATIONS

PICCOLO	SEAP-12-150	SEAP-24-250
Battery input (V)	12	24
Continuous power (W)	150	250
10-minute rating (W)	195	350
Surge power (W)	400	675
Peak efficiency (%)	92	93
Minimum battery size (Ah)	60	80
Weight (kg)	2.0	3.0
Size (mm) LxWxD	190 x 110 x 75	

• All specifications are at 30°C and unity power factor. See page xx for further specifications.